



**WISE-7167** 

8-Channel Power Relay Output PoE Module

#### Features

- Built-in Web Server for IF-THEN-ELSE rule setting
- Built-in IF-THEN-ELSE rule enigne for logic operation
- No more programming. Just click and get done!
- Support IO, Counter, Timer, Email operations
- Modbus/TCP Protocol for SCADA Software Seamless Integration
- IEEE 802.3af-compliant Power over Ethernet (PoE)
- 10/100 Base-TX Ethernet
- 2-way Isolation/ESD Protection
- DO Type: 8 Power Relay (Form A)











## ■ Introduction

WISE (Web Inside, Smart Engine) is a product series developed by ICP DAS that functions as control units for use in remote logic control and monitoring in various industrial applications, WISE offers a user-friendly and intuitive web site interface that allows users to implement IF-THEN-ELSE control logic on controllers just a few clicks away; no programming is required. With its powerful and easy-to-use features, it will minimize the learning curve, shorten time to market and dramatically reduce the effort and cost spent on system development.

WISE-7167 follows IEEE 802.3af-compliant (classification, Class 1) Power over Ethernet (PoE) specification. It allows receiving power from PoE enabled network by Ethernet pairs (Category 5 Ethernet cable). This feature provides greater flexibility and higher efficiency therefore simplifying systems design, saving space, reducing cables and eliminating the requirement for dedicated electrical outlets. Meanwhile, in case under a non-PoE environment, WISE-7167 will still be able to receive power from auxiliary power sources like AC adapters or battery, etc.

This module WISE-7167 supports Modbus/TCP protocol to make seamless integration with SCADA software available. It features 8-channel power relay outputs. Each power relay supports contact rating as 5 A @ 250 Vac or 5 A @ 30 Vpc.

## Applications -

Building Automation, Factory Automation, Machine Automation, Remote Maintenance, Remote diagnosis and Testing Equipment, etc.

## ☑ I/O Specifications.

| Relay Output |               |  |
|--------------|---------------|--|
| Output Cha   | annels        | 8  |
| Output Type  |               | Power Relay, Form A (SPST N.O.)                            |
| Operating '  | Voltage Range | 250 VAC/30 VDC   |
| Max. Load    | Current       | 5.0A/channel at 25 °C                                      |
| Operate Time |               | 6 ms   |
| Release Tir  | me            | 3 ms   |
| Electrical   | VDF           | 5A 250 V <sub>AC</sub> 30,000 ops (10 ops/minute) at 75 °C |
| Life         | VDE           | 5A 30 Vzc 70,000 ops (10 ops/minute) at 75 °C              |
| (Resistive   | UI            | 5A 250 Vac/30 Vac 6,000 ops.                               |
| Load)        | UL            | 3A 250 Vac/30 Vbc 100,000 ops.                             |
| Mechanical   | Life          | 20,000,000 ops. at no load (300 ops./minute)               |

## ■ System Specifications \_

| System                  |   |
|-------------------------|---|
| CPU                     | 80186 CPU (80 MHz)  |
| SRAM                    | 512 KB  |
| Flash Memory            | 512 KB  |
| EEPROM                  | 16 KB   |
| Dual Watchdog           | Yes   |
| Communication           |   |
| PoE Ethernet Port       | 10/100 Base-TX (With Link, Activity LED Indicator) and automatic MDI/MDI-X                |
| 2-Way Isolation         |   |
| Ethernet                | 1500 V <sub>DC</sub>  |
| Relay Output            | 3000 V <sub>rms</sub>   |
| LED Indicators          |   |
| PoE                     | PoE On  |
| L1                      | Run   |
| L2                      | Link/Act  |
| L3                      | 10/100M   |
| Power Requirements      |   |
| IEEE 802.3af            | Class 1   |
| Required Supply Voltage | Powered by Power over Ethernet (PoE) or auxiliary power +12 Voc ~ +48 Voc (non-regulated) |
| LED Indicator           | Yes   |
| Power Consumption       | 0.14 A @ 24 V∞ Max.   |
| Mechanical              |   |
| Dimensions (W x H x D)  | 72 mm x 123 mm x 35 mm  |
| Installation            | DIN-Rail or Wall mounting   |
| Environment             |   |
| Operating Temperature   | -25 °C ~ +75 °C   |
| Storage Temperature     | -30 °C ∼ +80 °C   |
| Humidity                | 5 ~ 90% RH, non-condensing  |

## Software Specifications

| Functions                   |  |
|-----------------------------|--|
| 36 IF-THEN-ELSE Logic Rules | 3 IF conditions with AND or OR operators<br>3 THEN actions<br>3 ELSE actions                       |
| 48 Internal Registers       | Hold temporary variables and read/write data via Modbus/TCP address.                               |
| 12 Timers                   | Delay / Timing functions.  |
| 12 Emails                   | Send Email messages to pre-set Email receivers.  |
| Rule Configuration Website  | Access Web server on WISE controllers to edit and upload logic rules through web browser.          |
| Modbus/TCP Protocol         | Real time control and monitoring I/O channels and system status of controllers via SCADA software. |

| nternal Register | = ` > ` < ` >= ` <=(value)          |
|------------------|-------------------------------------|
| OO Counter       | = ` > ` < ` >= ` <=(value) · Change |
| 'imer            | Timeout · Not Timeout               |



| THEN / ELSE Actions |                         |  |
|---------------------|-------------------------|--|
| DO Channel          | ON · OFF · Pulse Output |  |
| Internal Register   | Change the value        |  |
| DO Counter          | Reset                   |  |
| Timer               | Start · Stop            |  |
| Email               | Send                    |  |

## Pin Assignment \_\_\_\_\_

| RJ-45  01 RL6 NO 02 RL6 COM 03 RL7 NO 04 RL7 COM 05 N/A 06 N/A 07 N/A 08 (R)+Vs  | Terminal<br>No. | Pin<br>Assignment |
|--|-----------------|-------------------|
| 02 RL6 COM<br>03 RL7 NO<br>04 RL7 COM<br>05 N/A<br>06 N/A<br>07 N/A<br>08 (R)+Vs | E1              | RJ-45             |
| 03 RL7 NO<br>04 RL7 COM<br>05 N/A<br>06 N/A<br>07 N/A<br>08 (R)+Vs               | 01              | RL6 NO            |
| 04 RL7 COM<br>05 N/A<br>06 N/A<br>07 N/A<br>08 (R)+Vs                            | 02              | RL6 COM           |
| 05 N/A<br>06 N/A<br>07 N/A<br>08 (R)+Vs  | 03              | RL7 NO            |
| 06 N/A<br>07 N/A<br>08 (R)+Vs  | 04              | RL7 COM           |
| 07 N/A<br>08 (R)+Vs  | 05              | N/A               |
| 08 (R)+Vs  | 06              | N/A               |
|  | 07              | N/A               |
|  | 08              | (R)+Vs            |
| 09 (B)GND  | 09              | (B)GND            |




| Terminal<br>No. | Pin<br>Assignment |
|-----------------|-------------------|
| 23              | RL5 COM           |
| 22              | RL5 NO            |
| 21              | RL4 COM           |
| 20              | RL4 NO            |
| 19              | RL3 COM           |
| 18              | RL3 NO            |
| 17              | RL2 COM           |
| 16              | RL2 NO            |
| 15              | RL1 COM           |
| 14              | RL1 NO            |
| 13              | RL0 COM           |
| 12              | RL0 NO            |
| 11              | N/A               |
| 10              | N/A               |

## ✓ Wire Connection \_\_\_\_\_

| Digital<br>Output | Readback as 1                                | Readback as 0  |  |
|-------------------|--|--|--|
|                   | Relay On                                     | Relay Off  |  |
| Relay<br>Output   | RLx.COM Relay Close  ACODC To other channels | RLx.COM Relay Open Relay Open RLx.NO To other channels |  |

# Dimensions (Unit: mm) \_\_\_\_\_



## Ordering Information \_\_\_\_

WISE-7167 8-Channel Power Relay Output PoE Module (RoHS)

## Accessories \_\_\_\_\_

| GPSU06U-6    | 24V/0.25A, 6 W Power Supply                            |
|--------------|--|
| MDR-20-24    | 24V/1A, 24 W Power Supply with DIN-Rail Mounting       |
| NS-205 CR    | Unmanaged 5-Port Industrial Ethernet Switch (RoHS)     |
| NS-205PSE CR | Unmanaged 5-Port Industrial PoE Ethernet Switch (RoHS) |