



Unit: mm

## Specifications

|                                      |  |
|--------------------------------------|--|
| <b>SoC</b>                           | DM&P SoC CPU Vortex86SX- 300MHz<br>Real Time Clock with Lithium Battery Backup   |
| <b>Cache</b>                         | L1:16K I-Cache, 16K D-Cache  |
| <b>Bus</b>                           | 16-bit x-ISA interface   |
| <b>BIOS</b>                          | AMI BIOS   |
| <b>System Memory</b>                 | 128MB DDR2 Onboard   |
| <b>Watchdog Timer 0 &amp; 1 Sets</b> | Software programmable from 30.5 $\mu$ sec. to 512 sec.<br>x 2 sets (Watchdog 1 fully compatible with M6117D)   |
| <b>Flash Disk Support</b>            | Onboard 2MB SPI Flash Disk   |
| <b>I/O Interface</b>                 | RS-232 port x2<br>Parallel port x1<br>16-bit GPIO port x1  |
| <b>Connectors</b>                    | 2.0mm 64-pin header for 16-bit x-ISA interface x1<br>2.0mm 64-pin header for I/O interface x1<br>2.0mm 9-pin header for DMA x1<br>1.25mm 6-pin wafer for JTAG x1 |
| <b>Power Requirement</b>             | Single Voltage +5V @ 240mA   |
| <b>Weight</b>                        | 21g  |
| <b>Board Size</b>                    | 65 X 45mm (2.56 x 1.77 inches)   |
| <b>Operating Temperature</b>         | -20°C ~ +70°C<br>-40°C ~ +85°C (Optional)  |

## Packing List

- VSX-6119 x1

## Ordering information

- VSX-6119** Vortex86SX Mity-SoC CPU Module with 128MB DDR2
- VSX-6119-1** Mity-SoC Development Board
- ICOP-6019-VGA** Mity-SoC VGA/LCD Development Kit

## Mity-SoC Module

Mity-SoC Module (65 x 45mm) is designed as the kernel of your own application, which integrates the Vortex86SX CPU, onboard 128MB DDR2, BIOS and multi I/O. The I/O interface of Mity-SoC are 64-pin (2x32, pitch 2.0mm) connector x2; one is for x-ISA bus, another is for all I/O functions which including RS-232, Printer, and GPIO.

For assisting users easily use our Mity-SoC Module, ICOP provides complete development kit of Mity-SoC Development Board and Mity-SoC VGA/LCD Development Kit for Mity-SoC Module.

We also supply our customers with referential circuit diagram for easing user's effort during development process. Meanwhile, you can design your own based board which only equips I/O functions you need.

Please visit our website for getting further information you need:

<http://www.dmp.com.tw/tech/vortex86sx/>

You also can contact us for getting referential circuit drawing: [info@icop.com.tw](mailto:info@icop.com.tw)

## Mity-SoC CPU Module Ordering Selection

| Ordering Type No. | SPI-2MB | TTL | RS-232 |
|-------------------|---------|-----|--------|
| <b>VSX-6119-A</b> |         | V   |        |
| <b>VSX-6119-B</b> |         |     | V      |
| <b>VSX-6119-C</b> | V       | V   |        |
| <b>VSX-6119-D</b> | V       |     | V      |